



KONICA MINOLTA

Giving Shape to Ideas

bizhub i-SERIES FASTER WORKING RETHINK SPEED



OPTIONS

1 ENHANCED FEATURES

Serverless Pull Printing
LK-114

2 CONNECTIVITY

Wireless LAN
UK-221

USB I/F kit
EK-P08

USB I/F kit
EK-P09

NFC kit
EK-P10

I/F cable for CSRC modem
EK-P11

Biometric authentication
AU-102

ID card reader

Mount kit
MK-P08

3 OTHERS

Working table
WT-P03

10-Key pad
KP-P03

Keyboard holder
KH-P02

Mount kit
MK-P09

4 MEDIA INPUT

Paper tray
PF-P20

Height adjustment unit
PF-P22

Copy desk
DK-P04x

5 MEDIA OUTPUT

Off-line stapler
FS-P04



bizhub C4000i / C3300i Color A4 printer

FINISHING FUNCTIONALITIES

LEGEND

Mandatory option

Option

This option can only be installed with the respective option above it



Duplex



Corner
stapling
(offline)

TECHNICAL SPECIFICATIONS

SYSTEM SPECIFICATIONS

Print size/resolution	7" / 800 x 480
System memory (standard/max)	4,096 MB
System hard disk	8 GB (standard)
Interface	10/100/1,000-Base-T Ethernet; USB 2.0; Wi-Fi 802.11 b/g/n (optional)
Paper input capacity (standard/max)	600 sheets/1,600 sheets
Paper tray input (standard)	1x 500 sheets; A6-A4; custom sizes; 60-210 g/m ²
Paper tray input (optional)	1x 500 sheets; A4; 60-90 g/m ² 1x 500 sheets; A4; 60-90 g/m ²
Manual bypass	100 sheets; A6-A4; Custom sizes; 60-210 g/m ²
Automatic duplexing	B5-A4; 60-210 g/m ²
Finishing modes (optional)	Group; Sort; Staple (optional)
Output capacity (standard)	Max. 250 sheets
Power consumption	220-240 V / 50/60 Hz; Less than 1.45 kW
System dimension (W x D x H)	420 x 528 x 473 mm (without options)
System weight	Approx. 33.2 kg (without options)

PRINTER SPECIFICATIONS

Imaging technology	Laser
Toner technology	Simitri® HD polymerised toner
Print resolution	1,800 (equivalent) x 600 dpi; 1200 x 1200 dpi
Print Speed A4 (mono/colour)	Up to 40/40 ppm., Up to 30/30 ppm
1st print out time A4 (mono/colour)	8.0/8.7 sec., 8.7/ 9.6 sec.
Warm-up time	Approx. 13 sec. in mono; 15 sec. in color ²
Page description language	PCL 6 (XL3.0); PCL 5c; PostScript 3 (CPSI 3016); XPS
Operating System	Windows 7 (32/64); Windows 8/8.1 (32/64); Windows 10 (32/64); Windows Server 2008 (32/64); Windows Server 2008 R2; Windows Server 2012; Windows Server 2012 R2; Windows Server 2016; Windows Server 2019; Macintosh OS X 10.10 or later; Unix; Linux; Citrix
Printer fonts	80 PCL Latin; 137 PostScript 3 Emulation Latin
Mobile printing	AirPrint (iOS); Mopria (Android); Konica Minolta Mobile Print (iOS/Android/Windows 10 Mobile); Mobile Authentication and Pairing (iOS/Android) Optional: Google Cloud Print; WiFi Direct

DESCRIPTIONS

ENHANCED FEATURES

LK-114 Serverless Pull Printing	Secure and Follow Me printing solution requiring no server application
CONNECTIVITY	
UK-221 Wireless LAN	Wireless LAN and wireless LAN Access Point Mode
EK-P08 USB I/F kit	USB keyboard connection
EK-P09 USB I/F kit	USB keyboard connection; Bluetooth
EK-P10 NFC interface	To connect with Android mobile devices
AU-102 Biometric authentication	Finger vein scanner
ID card reader	Various ID card technologies
MK-P08 Mount kit	Installation kit for ID card reader

OTHERS

WT-P03 Working table	Authentication device placement
KP-P03 10-Key pad	For use instead of touchscreen
KH-P02 Keyboard holder	To place USB keyboard
CU-202 Air cleaning unit	Improving indoor air quality by reduced emissions
MK-P09 Mount kit	Installation kit for Air cleaning unit

MEDIA INPUT

PF-P20 Paper tray	500 sheets, A4, 60-90 g/m ²
PF-P22 Height adjustment unit	To achieve comfortable height for operation
DK-P04x Copier desk	Provides storage space for print media and other materials

MEDIA OUTPUT

FS-P04 Off-line stapler	20-sheet of-line stapling
--------------------------------	---------------------------

SYSTEM FEATURES

Security Functions (standard)	ISO 15408 HCD-PP Common Criteria (in evaluation); IP filtering and port blocking; SSL2; SSL3 and TLS1.0/1.1/1.2 network communication; IPsec support; IEEE 802.1x support; User authentication; Authentication log; Secure print; Kerberos; Print user data encryption
Accounting (standard)	Up to 100 user accounts; Active Directory support (user name + password)
Accounting Functions (optional)	Biometric authentication (finger vein scanner); ID card authentication (ID card reader); Authentication by mobile device (Android/iOS)
Software	Net Care Device Manager; Data Administrator; Web Connection; Print Status Notifier; Driver Packaging Utility; Log Management Utility



² Warm-up time may vary depending on the operating environment and usage

- All specifications refer to A4-size paper of 80 g/m² quality.
- The support and availability of the listed specifications and functionalities varies depending on operating systems, applications and network protocols as well as network and system configurations.
- Some of the product illustrations contain optional accessories.
- Specifications and accessories are based on the information available at the time of printing and are subject to change without notice.
- Konica Minolta does not warrant that any specifications mentioned will be error-free.
- All brand and product names may be registered trademarks or trademarks of their respective holders and are hereby acknowledged.

Product appearance, configuration and/or specifications are subject to change without notice. This product is not available for some countries or regions.

KONICA MINOLTA, symbol mark, Giving Shape to Ideas, AccurioLabel, AccurioPro, Simitri, S.E.A.D. and KONICA MINOLTA OPTIMIZED PRINT SERVICES

are registered trademarks or trademarks of KONICA MINOLTA, INC.

Windows and Windows Server are registered trademarks or trademarks of Microsoft Corporation in the U.S. and other countries.

Adobe and PostScript are registered trademarks or trademarks of Adobe Systems Inc.

Mac OS is registered trademark or trademark of Apple Inc.

All other brands and product names are registered trademarks or trademarks of their respective companies or organisations.



From consulting, system design, to operations, Konica Minolta offers total support to optimise your office output environment.

<http://www.bt.konicaminolta.a.in>

⚠ Requirements for safe use

Please read and follow the instruction manual to ensure safe operation. Only operate using appropriate power supply and voltage. Connecting the earth wire to an inappropriate place may cause explosion or electric shock. Please connect accordingly (Taiwan and the Philippines only).



Konica Minolta Business Solutions India Pvt. Ltd.

Building No: 8, Tower-C, 10th Floor, DLF Cyber City, Phase-2, Gurugram, Haryana-122002, India | Board No. +91-124-6652000

URL: www.konicaminolta.in | marcom@bin.konicaminolta.in | Connect with us: